



Product data sheet

Power tools for trade & industry

Radio

GPB 18VH-6 SRC



Powerful jobsite radio with charging function that boosts your workplace – for 12V and 18V batteries

The most important data

Input voltage(s), mains	220 – 240 V
Radio frequency range FM	87.5 – 108 MHz

Part Number 0 601 4A6 270

Technical data

Technical data

Radio frequency range FM	87.5 – 108 MHz
Radio frequency range DAB+	174.928 – 239.2 MHz
Station presets FM	5
Station presets DAB+	5
Input voltage(s), mains	220 – 240 V
Weight excl. battery	8.2 kg
Packaging dimensions (width x length x height)	253 x 485 x 360 mm
Battery voltage	12 V Li-ion battery, 18 V Li-ion battery
Bluetooth® type	Bluetooth 5.4
Bottle opener	Yes
Charge level indicator	Yes
External power supply included	No
L-Boxx compatibility	Yes
Integrated battery charger	12.0 V, 18.0 V
Multi-Speaker Sound	Yes
Nominal output per mid-range speaker	24 W
Nominal output of subwoofer	40 W
No of USB charging ports	1
Protective frame	Yes
USB charging	Yes

Subwoofer	Yes
Bluetooth®	Yes
IP protection type	IP54
Max.In-tool charging current	2 A
Number of speakers	2
Radio source	DAB+, FM



BOSCH

Invented for life

Product data sheet

Power tools for trade & industry

Advantages:

- Enjoy outstanding sound with DAB+, FM, Bluetooth®, AUX as well as Multi-Speaker Sound
- Charge your 12V and 18V batteries when the jobsite radio is running on mains
- L-BOXX compatibility makes it easy for you to transport your radio to every jobsite

